Anritsu Site Master S820C Specs Provided by www.AAATesters.com

## **/Inritsu**

Bit/Master T

# Site Master™ \$810C/\$820C

Microwave Transmission Line and Antenna Analyzer 3.3 GHz to 10.5 GHz/3.3 GHz to 20 GHz

SimManter S

THE PER MANY

Anatsu

SiteMaster The World's Leading Handheld Microwave Transmission Line and Antenna Analyzer

## The Leading Microwave Transmissic

Anritsu's hand held, battery operated Microwave Site Master is the most accurate and convenient tool available for field installation, verification, troubleshooting and repair of microwave communication systems. Difficult test specifications become easy to verify. The S800 "C" Series improves quality and reduces maintenance expenses by providing vector corrected measurements via calibration and a convenient user interface.

Microwave Site Master targets microwave site installers, point-to-point operators, point-to-multipoint operators, radio manufacturers, PCS/Cellular operators, utility companies and private/public networks that support microwave links. These microwave Site Master models test both waveguide and coaxial cables more conveniently than laboratory sized scalar analyzers or microwave test sets.

#### **Vector Error Correction**

Vector error correction within the S800 "C" Series improves the quality and convenience of measurements compared to traditional scalar techniques. Accuracy and repeatability are enhanced as errors such as test port match and source match are accounted for.



#### Waveguide Calibration

The test port connection to the waveguide under test is a small coaxial-to-waveguide adapter rather than a bulky coupler.

The calibration components include two offset shorts,  $\frac{1}{8}$  and  $\frac{3}{8}$  wave-length, and a precision waveguide load. The two offset shorts eliminate reference error suffered by scalar systems where only a single waveguide short is used to determine the 0.0 dB reflection reference level. Site Master's flange design mates to square, rectangular or circular flanges. For a given waveguide size, only one calibration set is required. Site Master's waveguide calibration components are built with precision alignment pins that mate the companion coaxial-to-waveguide adapters. As a result, proper alignment to the waveguide is fast and convenient.

#### Waveguide Dispersion

Vector error correction also improves the quality of Distance-To-Fault data. Not only is the reflection magnitude more accurate, but the waveguide dispersion correc-

tion for fault location (different frequencies propagate at different speeds) is more accurate and repeatable. The post-vector corrected data accounts for the non-dispersive length of coaxial cable preceding the input of the waveguide under test. Unlike scalar-based systems, the **Microwave Site Master** S800 "C" Series does not suffer reflection magnitude errors and length inaccuracies in proportion to the relative lengths of the coaxial input cable and waveguide under test.



#### Tune Mode

Tune Mode is a fast sweep mode used to quickly tune the waveguide by adjusting the flange connectors quickly at both ends of the waveguide.

There are three levels of resolution available for tune mode; 65, 43, and 33 data points. The higher the number of data points, the greater the measurement resolution.

#### Easy-to-Use

Site Master's S800 "C" Series menu driven interface requires little training and simplifies the field engineers' and technicians' task of deployment, site-to-site maintenance and trouble-shooting by identifying, recording and solving problems without sacrificing measurement accuracy.

- Store ten test setups for fast, repeatable testing.
- Store up to 200 measurement traces in nonvolatile memory
- Multilingual user interface features on screen menus and messages in 7 different languages English, German, French, Spanish, Portuguese, Chinese, and Japanese.

## on Line and Antenna Analyzer

### Site Master S800 "C" Series for Microwave Applications

#### Powerful Data Analysis Software

Powerful data analysis software comes with every Site Master unit, providing users with an easy method of analyzing system performance, trends and problems in addition to professional report generation.

- Site Master PC software is Windows 95/98/NT4/2000/ME/XP workstation compatible and supports alpha-numeric file names for descriptive data labeling.
- Store an unlimited number of data traces for comparison to historical performance.
- Quickly and easily download data traces from the Site Master to a PC database with a single menu selection.

#### Accurate, Repeatable Measurements

Utilizing vector error correction, Site Master delivers accurate, reliable and repeatable Return Loss/VSWR and Fault Location measurements. Site Master's high immunity to interference allows users to conduct measurements of an active site without loss of accuracy.

- Locate long range problems with 517 data points.
- Superior immunity to on-channel interference for testing at co-located antenna sites.
- Large, high-resolution display allows for easy viewing and trace interpretation under a variety of conditions.
- Full range of marker and limit functions facilitate quick, comprehensive measurements.

#### Measurement Accuracy Return Loss and SWR

Accuracy  $\leq 1.3 + |20 \log (1 \pm 10^{-E_{\Delta/20}})| dB$ , typical. where  $E_{\Delta} = Directivity$  - Measured Return Loss.

Directivity is the largest source of return loss measurement uncertainty. The quality of the load or termination used for calibration determines directivity performance. Loads can be verified using a vector network analyzer calibrated with either sliding load or TRL.

#### Specifications \*1

Frequency Range		S810C (3.3 to 10.5 GHz), S820C (3.3 to 20 GHz)	
Frequency Accuracy (CW mode)		±75 ppm @ +25°C	
Display Resolution		130, 259, 517 data points	
Immunity to interfering signals		–10 dBm	
Return Loss	Range	0 to 54 dB	
	Resolution	0.01 dB	
CIMP	Range	1 to 65	
SWR	Resolution	0.01	
	Vertical range	Return loss: 0 to 54 dB	
	Horizontal range (meter)	0 to (data points –1) x resolution to a maximum of 1000 m (3281 ft.) where data points = 130, 259, 517	
Distance-to-Fault	Horizontal resolution, rectangular windowing for coaxial cble (meter)	(1.5 x 10 <sup>s</sup> ) (υρ)/Δ frequency* <sup>2</sup>	
	Horizontal resolution for wave- guide	$\frac{1.5 \text{ x10}^{\circ} (\sqrt{1 - (F_c/F_1)^2})^{*3}}{\Delta F}$	
Coax/Waveguide	Range	0 to 54 dB	
Insertion Loss	Resolution	0.01 dB	
Test port connector		Precision K(f) or N(f)	
	Display range	-80 to +80 dBm	
RF power monitor,	Detector range	-45 to +20 dBm, 30nW to 100 mW	
(Option 5)	Offset range	0 to +60 dB	
	Resolution	0.1 dB, 0.1 x W	
Maximum input without damage	K(f) test port	+27 dBm	
Trace memory		up to 200 traces	
Instrument configuration	n with calibration memory	10 states	
Custom cable configuration memory		50 configurations	
Temperature	Operating	0 to 50°C	
Temperature	Storage	-20°C to 75°C	
Weight		1.89 kgs (4.2 lbs.)	
Size		25.4 x 17.8 x 6.10 cm (10 x 7 x 2.4 in.)	
General	Electromagnetic compatibility	Meets European community CE requirements	
	RS232	9 pin D-sub, three wire serial	

\*1: All Specifications apply when calibrated at ambient temperature after a five minute warm up.

\*2: Where υ<sub>p</sub> is the cable's relative propagation velocity, Δ frequency is the stop frequency minus the start frequency (in Hz). Wide frequency sweeps improve resolution but reduce maximum display range.

\*3: Where Fc is waveguide cutoff frequency (Hz); F1 is the start frequency (Hz);  $\Delta F$  is the stop frequency minus the start frequency (Hz).

#### **Key Features**

- · Accurately tests coaxial cable/waveguide transmission line and antennas
- · Tune mode for waveguide component alignment/testing
- Superior immunity to live site RF interference
- Clearly defined user interface for coaxial cable and waveguide media
- Pop up menus for cable list, waveguide list and compatible flange list
- Quickly select cable/waveguide type and test parameters without setup error
- Large, high resolution display allows for easy viewing and trace interpretation under a variety of conditions

### Calibration Components

XX represents Calibration components

- 23 = 1/8 Offset Short 24 = 3/8 Offset Short
- 24 = 3/8 Offset Sho
- 26 = Precision Load 35 = Coaxial to waveguide adapter
- N = N type connector K = K type connector ex: 35UA137N



#### Coaxial Calibration Components:

22N50 Precision Short/Open, N(m) up to 18 GHz 28N50-2 Precision Load, 40 dB, N(m) up to 18 GHz 22K50 Precision Short/Open, K(m) up to 40 GHz 28K50 Precision Load, 40 dB, K(m) up to 40 GHz

Precision Waveguide Calibration Components*1				
Part Number	Frequency Range	Waveguide Type	Compatible Flanges	
xxUM70	5.85 to 8.20 GHz	WR137, WG14	CAR70, PAR70, UAR 70, PDR70	
xxUM84	7.05 to 10.00 GHz	WR112, WG15	CBR84, UBR84, PBR84, PDR84	
xxUM100	8.20 to 12.40 GHz	WR90, WG16	CBR100, UBR100, PBR100, PDR100	
xxUM120	10.00 to 15.00 GHz	WR75, WG17	CBR120, UBR120, PBR120, PDR120	
xxUA187	3.95 to 5.85 GHz	WR187, WG12	CPR187F, CPR187G, UG-1352/U, UG-1353/U, UG-1728/U, UG-1729/U, UG-148/U, UG-149A/U	
xxUA137	5.85 to 8.20 GHz	WR137, WG14	CPR137F, CPR137G, UG-1356/U, UG-1357/U, UG-1732/U, UG-1733/U, UG-343B/U, UG-344/U, UG-440B/U, UG-441/U	
xxUA112	7.05 to 10.00 GHz	WR112, WG15	CPR112F, CPR112G, UG-1358/U, UG-1359/U, UG-1734/U, UG-1735/U, UG-52B/U, UG-51/U, UG-137B/U, UG-138/U	
xxUA90	8.20 to 12.40 GHz	WR90, WG16	CPR90F, CPR90G, UG-1360/U, UG-1361/U, UG-1736/U, UG-1737/U, UG-40B/U, UG-39/U, UG-135/U, UG-136B/U	
xxUA62	12.40 to 18.00 GHz	WR62, WG18	UG-541A/U, UG-419/U, UG-1665/U, UG1666/U	
xxUA42	17.00 to 26.50 GHz	WR42, WG20	UG-596A/U, UG-595/U, UG-597/U, UG-598A/U	
Precision Waveguide-to-Coaxial Adapters*1				
35UM70N	5.85 to 8.20 GHz	WR137, WG14	CAR70, PAR70, UAR 70, PDR70	
35UM84N	7.05 to 10.00 GHz	WR112, WG15	CBR84, UBR84, PBR84, PDR84	
35UM100N	8.20 to 12.40 GHz	WR90, WG16	CBR100, UBR100, PBR100, PDR100	
35UM120N	10.00 to 15.00 GHz	WR75, WG17	CBR120, UBR120, PBR120, PDR120	
35UA187N	3.95 to 5.85 GHz	WR187, WG12	CPR187F, CPR187G, UG-1352/U, UG-1353/U, UG-1728/U, UG-1729/U, UG-148/U, UG-149A/U	
35UA137N	5.85 to 8.20 GHz	WR137, WG14	CPR137F, CPR137G, UG-1356/U, UG-1357/U, UG-1732/U, UG-1733/U, UG-343B/U, UG-344/U, UG-440B/U, UG-441/U	
35UA112N	7.05 to 10.00 GHz	WR112, WG15	CPR112F, CPR112G, UG-1358/U, UG-1359/U, UG-1734/U, UG-1735/U, UG-52B/U, UG-551/U, UG-137B/U, UG-138/U	
35UA90N	8.20 to 12.40 GHz	WR90, WG16	CPR90F, CPR90G, UG-1360/U, UG-1361/U, UG-1736/U, UG-1737/U, UG-40B/U, UG-39/U, UG-135/U, UG-136B/U	
35UA62N	12.40 to 18.00 GHz	WR62, WG18	UG-541A/U, UG-419/U, UG-1665/U, UG1666/U	
35UA42K	17.00 to 26.50 GHz	WR42, WG20	UG-596A/U, UG-595/U, UG-597/U, UG-598A/U	

Precision N(m) to N(m) Adapter, 18 GHz

Precision Adapter, K(m) to K(m), 40 GHz

Automotive Cigarette Lighter/12 Volt DC Adapter

HP DeskJet Printer, Model 450: Includes printer cable, 2000-1216 black print cartridge and U.S. power cord. Also includes 2000-753 serial-to-parallel Centronics converter cable and 1091-310 Centronics-to DB25 adapter. Rechargeable battery is optional and

Null Modem Serial-to-Parallel Centronics Converter Cable

Adapter 36-pin Centronics female-to-DB25 female

Rechargeable Battery for DeskJet Printer, Model 450

Power Cable (Europe) for DeskJet Printer

Power Cable (Japan) for DeskJet Printer

Power Cable (U.K.) for DeskJet Printer

Power Cable (Australia) for DeskJet Printer

Power Cable (S. Africa) for DeskJet Printer

Precision Adapter, K(f) to K(f), 40 GHz

Transit Case for Microwave Site Master

Site Master S810C/S820C User's Guide

Anritsu Handheld Software Tools

USB to RS232 Adapter Cable

Precision N(f) to N(f) Adapter, 18 GHz

5W Attenuator, N(m) to N(f), 18 GHz

Detector Extender Cable, 7.6 m

Rechargeable NiMH Battery

Soft Carrying Case

Battery Charger (Ext.)

Serial Interface Cable

AC/DC Adapter

is not included

Black Print Cartridge

\*1 Contact an Anritsu sales representative for availability of the waveguide calibration components and waveguide-to-coaxial adapters not listed in the table.

34NN50A

34NFNF50

42N50-20

800-109

K220B

K222B

D41955

40-115

633-27

806-62

800-441

760-213

2300-347

551-1691

Printers 2000-1214

2000-753

1091-310

2000-1216

2000-663

2000-664

2000-666

2000-667

2000-1217

2000-1218

10580-00076

2000-1029

### **Ordering Information**

Model S810C(3.3 GHz to 10.5 GHz), Built-in DTF, K(f) Test Port ConnectorModel S810C/11NF(3.3 GHz to 10.5 GHz), Built-in DTF, N(f) Test Port ConnectorModel S820C(3.3 GHz to 20.0 GHz), Built-in DTF, K(f) Test Port ConnectorModel S820C/11NF(3.3 GHz to 20.0 GHz), Built-in DTF, N(f) Test Port ConnectorModel S820C/11NF(3.3 GHz to 20.0 GHz), Built-in DTF, N(f) Test Port Connector

#### Standard Accessories:

User's Guide Soft Carrying Case AC-DC Adapter Precision Adapter, Ruggedized K(m) to N(f), (S810C and S820C models only) Automotive Cigarette Lighter/12 Volt DC Adapter Handheld Software Tools CD ROM containing Fault Location (DTF) Smith Chart and Software Management Serial Interface Cable Rechargeable Battery, NiMH

#### Optional Accessories:

Option 5 Option 11NF	RF Power Monitor (RF Detector not included) N(f) Test Port Connector
560-7N50B	RF Detector, N(m), 50 $\Omega$ , 10 MHz to 20 GHz
22N50	Precision N(m) Short/Open, 18 GHz
22NF50	Precision N(f) Short/Open, 18 GHz
22K50	Precision K(m) Short/Open, 40 GHz
22KF50	Precision K(f) Short/Open, 40 GHz
28K50	Precision Termination, DC to 40 GHz, $50\Omega$ , K(m)
28KF50	Precision Termination, DC to 40 GHz, 50 $\Omega$ , K(f)
28N50-2	Precision Termination, DC to 18 GHz, 50 $\Omega$ , N(m)
28NF50-2	Precision Termination, DC to 18 GHz, 50 $\Omega$ , N(f)
34RKNF50	Precision Adapter, Ruggedized K(m) to N(f)
15NNF50-1.5B	Armored Test Port Cable, 1.5 meter N(m) to N(f) 18 GHz
15KKF50-1.5A	Armored Test Port Cable, 1.5 meter K(m) to K(f) 20 GHz
15RKKF50-1.5A	Ruggedized Armored Test Port Cable, 1.5 meter
	K(m) to K(f) 20 GHz

Spectrum Master " Cell Master

#### SALES CENTERS:

United States (800)	ANRITSU
Canada (800) ANR	ITSU
South America 55 (	(21) 286-9141

Europe 44 (0) 1582-433433 Japan 81 (46) 223-1111 Asia-Pacific (65) 6282-2400 Microwave Measurements Division 490 Jarvis Drive, Morgan Hill, CA 95037-2809 http://www.us.anritsu.com



©Anritsu March, 2004. All trademarks are registered trademarks of their respective companies. Data is subject to change without notice. For most recent specifications visit www.us.anritsu.com Discover What's Possible®