



## OLP-34/35/38

### SmartPocket™ Optical Power Meters

Viavi Solutions® OLP-3x optical power meters quickly, easily, and conveniently measure power levels and loss in fiber networks.

#### Pocket-Sized Power Meters for All Kinds of Applications

Easy-to-use for technicians at any skill level, SmartPocket optical power meters complement Viavi optical light sources for insertion loss and continuity testing in both multimode and single-mode networks. They offer a dedicated and cost-optimized solution for testing and troubleshooting fiber in the field with:

- Intuitive, one-button operation
- Automatic wavelength recognition
- A large, sharp display that simultaneously shows relevant results and settings

The small and rugged OLP-3x also includes unprecedented data storage capacity and downloads results to a PC with a micro USB port.

- The OLP-34 is optimized for LAN/WAN access and enterprise networks and multimode or single-mode applications
- The OLP-35 is optimized for standard telecommunication network applications
- The OLP-38 is a higher-power (+26 dBm) version for CATV (with analog RF transmission) or amplified DWDM systems applications

#### Key Benefits

- Cost-effective, rugged high-performance solution
- 3-year recalibration period
- 1 nm incremental universal wavelength settings
- Universal optical interface supports all 2.5 mm with an option to support 1.25 mm connectors
- Auto wavelength detection and TwinTest mode
- Internal data storage and PC download capability
- Quick start operation eliminates warm-up

#### Applications

- Measuring optical power levels and link insertion loss
- Enterprise LAN networks with 850/1300 nm multimode wavelengths capability
- Test access and metro (LAN/WAN) networks in multimode and single-mode
- Standard and high-power level tests for use in telecom, CATV, and military applications

## A Small Tool with Big Capabilities

Large, sharp screen displays:

- Battery level status
- Power mode (PERM, ECON)
- Measurement results in dBm/W/dB
- Wavelength setting
- Auto wavelength detection
- Tone detection

Straightforward 4-button operation



Rugged, shock resistant, and splash-proof design

3-way power

- AA dry
- AA rechargeable
- AC operation



## Test and Report Field Measurements

Viavi Smart Reporter reporting software lets users quickly and efficiently download test results data from the power meter's memory with just a few clicks. After it's downloaded, the software reporting functions let users generate and customize professional



Report date: Tuesday, 7. June 2016

### OLP-34/35/38 Report - my Report 01

#### Technician Information

Company Name: Viavi  
 Technician Name: Mustermann  
 Address: Altbachstr. 5  
 Postal Code: 72500  
 City: Ermingen  
 Country: Germany



#### Measurement results

Fiber ID	λ [nm]	Power [dBm]	Power [µWatt]	Power [dB]	Reference [dBm]	Mod.Freq. [Hz]
5	1310			-4.57	-3.26	
7	1490			-4.19	-3.07	
8	1310			-6.62	-3.26	270
9	1310			-4.10	-3.26	1000
10	1550			-4.13	-3.46	1000
11	1550	-3.98				
12	1550	-3.98				
13	1310	-4.33				
14	1310		309.30			
15	1550		400.90			

SmartPocket OMK-3x optical test kits include an OLS-3x optical light source, an OLP-3x optical power meter, and accessories

## Technical Specifications

	OLP-34	OLP-35	OLP-38
Detector type	InGaAs	InGaAs	Filtered InGaAs
Optical interface/connectors	Universal 2.5 mm/1.25 mm <sup>1</sup>	Universal 2.5 mm/1.25 mm <sup>1</sup>	Universal 2.5 mm/1.25 mm <sup>1</sup>
Wavelength range	780 to 1600 nm	780 to 1650 nm	780 to 1650 nm
Wavelength settings	780 to 1600 nm, step size 1 nm	780 to 1650 nm, step size 1 nm	780 to 1650 nm, step size 1 nm
Programmable wavelengths	5 presets (customized)	5 presets (customized)	5 presets (customized)
Calibrated wavelengths	850, 980, 1310, 1490, 1550 nm	850, 980, 1310, 1490, 1550, 1625 nm	850, 980, 1310, 1490, 1550, 1625 nm
Power range	-60 to +5 dBm	-65 to +10 dBm	-50 to +26 dBm
Display range	-60 to +10 dBm	-65 to +13 dBm	-50 to +26 dBm
Max. input power	+13 dBm	+16 dBm	+27 dBm
Measurement units	dB/dBm/W	dB/dBm/W	dB/dBm/W
Intrinsic uncertainty <sup>2</sup>	±0.2 dB (±5%)	±0.2 dB (±5%)	±0.2 dB (±5%)
Linearity <sup>3</sup>	±0.06 dB (-50 to +5 dBm)	±0.06 dB (-50 to +5 dBm)	±0.06 dB (-32 to +20 dBm)
Tone detection	270 Hz, 1 kHz, 2 kHz	270 Hz, 1 kHz, 2 kHz	270 Hz, 1 kHz, 2 kHz
Auto $\lambda$ mode <sup>4</sup>	Yes	Yes	Yes
Multi $\lambda$ mode <sup>4</sup>	TwinTest/serial TripleTest	TwinTest/serial TripleTest	TwinTest/serial TripleTest

### Notes:

- Optional 1.25 mm UPP accessory adapter is available.
- Under these reference conditions: -20 dBm (CW), 1310 nm  $\pm$ 1 nm, 23°C  $\pm$ 3K, 5 to 75% relative humidity 9 to 50  $\mu$ m test fiber with ceramic DIN connector.
- 5 to +45°C.
- With Viavi light sources.

General (typical at 25°C)	
<b>Storage and Interface</b>	
Data storage	100 results
Data download capability	Micro USB interface for PC transfer
<b>Power Supply</b>	
Dry batteries	2x Mignon (AA) 1.5 V
Rechargeable batteries	2x Mignon (AA) NiMH 1.2 V
AC operation	Via micro USB and SNT-505
Battery life	$\geq$ 200 hr Automatic power off after 20 minutes
<b>Environmental Conditions</b>	
EMI/ESD	CE compliant
Recommended calibration interval	3 years
Operating temperature	-10 to +55°C (+14 to +131°F)
Storage temperature	-40 to +70°C (-40 to +158°F)
Dimensions (H x W x D)	30 x 80 x 150 mm (1.2 x 3.1 x 5.9 in)
Weight	200 g (0.45 lb)

## Ordering Information

Description	Part Number
OLP-34 optical power meter InGaAs, +5 dBm with data storage and USB download capability	2302/11
OLP-35 optical power meter InGaAs, +10 dBm with data storage and USB download capability	2302/12
OLP-38 optical power meter Filtered InGaAs, +26 dBm with data storage and USB download capability	2302/13

Each optical power meter includes a 2.5 mm UPP adapter, AA alkaline batteries, a quick start guide, neck strap, a belt bag, and a USB connection cable.

Description	Part Number
<b>Optional Accessories</b>	
Fiber cleaning consumables kit	FCR-CLN-01
NiMH rechargeable batteries, Mignon AA, 1.2 V (2 batteries required)	2237/90.02
SNT-505; universal AC power adapter, micro USB connector	2302/90.01
UPP adapter for LC, MU (1.25 mm)	2256/90.03
USB connection cable	K 807
Smart Reporter (free download from <a href="http://www.updatemyunit.net/">http://www.updatemyunit.net/</a> )	



Contact Us **+1 844 GO VIAVI**  
(+1 844 468 4284)

To reach the Viavi office nearest you,  
visit [viavisolutions.com/contacts](http://viavisolutions.com/contacts).

© 2016 Viavi Solutions, Inc.  
Product specifications and descriptions in this document are subject to change without notice.  
OLP-34-35-38-ds-fop-tm.ae  
30162955 905 0716